



LoRaWAN™ compatible STREET LIGHTING REMOTE MANAGEMENT & SMART CITY PLATFORM

[FRCM-L - LoRaWAN™ compatible lighting panel control and monitoring unit - data sheet]

December 3, 2018

Ver 1.3

FRCMv4-L - LoRaWAN™ compatible LIGHTING PANEL CONTROL and MONITORING UNIT

Installed inside the feeder pillar, it is designed to provide autonomous operation for street lighting installations and to carry out three phase measurements and analysis of electrical parameters in street lighting grids.

- › Specially designed and optimized **for LoRaWAN™** (long range RF wide area networks).
- › **VPN security** with AES128/256-bit encryption and key rotation.
- › **Bandwidth efficient** with minimal communication requirements.
- › **Autonomous operation** based on predefined astronomic calendar and/or external light level sensor (digital INPUT).
- › **Remote real-time ON/OFF control.**
- › **Remote monitoring** of grid parameters in street lighting grids: per phase voltage, current, frequency, power factor, active/ reactive/ apparent power, daily active/ reactive energy consumption.
- › **Configuration options** for: current transformer ratio, voltage/power thresholds and daytime/nighttime consumption thresholds.
- › **LCD** for displaying electrical parameters and device status.
- › **GPS** for exact location and time.
- › **Maintenance switch** for local manual override (AUTO/ON/OFF).
- › **Inputs:** 2 x Digital INPUT.
- › **Output:** 1 x Dry contact relay output (230V, max 12A).
- › Designed **lifetime: 10+** years.



LoRaWAN™ Class A
Compatible

LoRaWAN™ Class C
Compatible

inteliLIGHT® is a registered trademark of FLASHNET | LoRaWAN™ is a registered trademark of Semtech



FLASHNET





LoRaWAN™ compatible STREET LIGHTING REMOTE MANAGEMENT & SMART CITY PLATFORM



[FRCM-L - LoRaWAN™ compatible lighting panel control and monitoring unit - data sheet]

December 3, 2018

Ver 1.3



PLUG & PLAY
ADAPTABLE
to EXISTING
STREET LIGHTING
INFRASTRUCTURE

**SCALABLE &
IMMEDIATELY
OPERABLE**



up to
35%
ENERGY
SAVINGS



up to
42%
MAINTENANCE
COST REDUCTION

FRCMv4-L - lighting panel control and monitoring unit

Product description	Street lighting panel control and monitoring unit
Power supply	Direct connection
Power consumption	Max. 10 W
Network interface	LoRaWAN™ (low power, long range radio frequency)
Communication protocol	LoRaWAN™: Class C or Class A
RF spectrum	868MHz / 915MHz / 923MHz
Security	AES128/256-bit encryption and key rotation per session
Voltage input range	0V - 265V / 45-65 Hz
Input	R, S, T voltage inputs R, S, T, N current inputs 2 x Digital input
Power network type	Three phase electric network and Neutral
Current transformers	Standard X:5, where X is user definable
Operating temperature	-25°C to + 80°C
Operating humidity	95% non-condensing
Connectors	Voltage (R,S,T,N), Current (R,S,T,N), RF / GPS / USB
Grid connectors	2.5 mm ² terminals
Antennas	2 x SMA
Output	1 x Dry contact relay (230V, max 12A)
Display	LCD
Precision Real Time Clock (RTC)	Battery operated
Battery operation time	Up to 12 hours
GPS	Location and time
Dimensions (L x W x H)	138 x 90 x 47 mm
IP rating	IP42 (optional IP67 external housing)
Certifications	CE FCC (in progress)

MEASUREMENTS:

- › voltage
- › current
- › active power
- › reactive power
- › apparent power
- › active energy
- › reactive energy
- › power factor
- › frequency

CONFIGURABLE PARAMETERS:

- › current
- › transformer ratio
- › voltage/power /
current thresholds
- › daytime/
nighttime
consumption
threshold

GENERATED ALARMS:

- › over/ under voltage
detection
- › over/ under power
detection
- › over/ under current
detection
- › unusual daytime/nighttime
consumption
- › phase failure



FLASHNET



14 Odem ST. P.O.B. 7042 Petach Tikva 4917001, ISRAEL | Office: +972-3-924-3352
Fax: +972-3-9243385 | sales@hypertech.co.il | www.hypertech.co.il