

Part Number	RF Frequency	Description	Rx Gain	Rx NF	Rx Current	Tx Gain	Saturated Output Power	Tx Current	Supply Voltage	Package
	(MHz)		(dB)	(dB)	(mA)	(dB)	(dBm)	(mA)	(V)	
<b>BFM4120</b>	2400-2500	ZigBee/Thread/Bluetooth FEM	11.5	2.6	8	24	21	75/90	2.7-3.6	16L 3 x 3 x 0.55mm QFN
<b>8TR1211</b>	2400-2500	Bluetooth FEM_PA, By Pass	-	-	-	14	17/15	15/23	2.7-3.6	16L 2 x 2 x 0.45mm QFN
<b>8TR1215</b>	2400-2500	Bluetooth FEM_PA, By Pass	-	-	-	15	11	9/17	1.5-2.3	8L 2 x 2 x 0.45mm QFN
<b>8TR1216</b>	2400-2500	Bluetooth FEM_PA, By Pass	-	-	-	13	10	8/18	2.0-3.6	8L 2 x 2 x 0.45mm QFN
<b>8TR2211</b>	2400-2500	ZigBee/Bluetooth FEM, LNA, By Pass	13/11	2/2.5	7/4	-	-	-	2.7-3.6	16L 2 x 2 x 0.45mm QFN
<b>8TR8201</b>	2400-2500	ZigBee/Thread/Bluetooth FEM	11.5	2.6	8	24	21	75/90	2.7-3.6	16L 3 x 3 x 0.55mm QFN
<b>8TR8202</b>	2400-2500	High Power ISM FEM	10.5	3.0	8.5	28/32	15/23	60/108/136	2.7-3.6	16L 3 x 3 x 0.55mm QFN
<b>8TR8210</b>	2400-2500	Bluetooth, Low Power FEM	12/11	2.5/3	8/5.5	23	20/21	75/85	2.7-3.6	16L 3 x 3 x 0.55mm QFN
<b>8TR8211</b>	2400-2500	Bluetooth FEM	13.0	2.3	8	12	12/13/14	15/23	2.7-3.6	16L 2 x 2 x 0.45mm QFN
<b>8TR1111</b>	850-930	Sub-GHz ISM Band FEM	-	-	-	34	24/23	260/100	2.7-3.6	16L 3 x 3 x 0.45mm QFN
<b>8TR1218</b>	2400-2500	Bluetooth FEM_PA, By Pass, Tx-Rx SW	-	-	-	9	12	8/24	2.0-3.6	8L 2 x 2 x 0.45mm DFN

<b>8TR1241</b>	2400-2500	Bluetooth FEM_4-port Antenna	-	-	-	11	12/13/14	17/22	2.7-3.6	20L 3 x 3 x 0.55mm QFN
Part Number	RF Frequency	Description	Rx Gain	Rx NF	Rx Current	Tx Gain	Saturated Output Power	Tx Current	Supply Voltage	Package
	(MHz)		(dB)	(dB)	(mA)	(dB)	(dBm)	(mA)	(V)	
<b>8TR7201</b>	2400-2500	Bluetooth, PA IC	-	-	-	22/23	21	80/18	1.8-3.6	8L 2 x 2 x 0.45mm QFN
<b>8TR8211C</b>	2400-2500	ZigBee/Bluetooth FEM LNA By Pass	13.0	2.4	4.5	12	12/13/14	15/23	2.7-3.6	16L 2 x 2 x 0.45mm QFN
<b>8TR8213</b>	2400-2500	Bluetooth FEM_PA/LNA	13.0	2.5	8	16	16	12/32	2.7-3.3	16L 2 x 2 x 0.45mm QFN
<b>8TR8220</b>	2400-2500	High Power ISM FEM	11/8	2.7/3	9/5	30	23	95/150	2.7-3.6	16L 3 x 3 x 0.55mm QFN
<b>8TR8241</b>	2400-2500	Bluetooth FEM_4-port Antenna	13/11	3.8/4.1	9.5/6	11	12/13/14	17/22	2.7-3.6	20L 3 x 3 x 0.55mm QFN



14 Odem ST. P.O.B. 7042 Petach Tikva 4917001, ISRAEL | Office: +972-3-924-3352  
 Fax: +972-3-9243385 | sales@hypertech.co.il | www.hypertech.co.il